
# DT Accessories DT-DBC4A1




## **DESCRIPTION**

2-wire system branch controller with four outputs.

## **DIMENSION**








## **FEATURES**


- 4 outputs branch controller;
- For multi door stations input(max.4);
- Separate isolation protection;
- Short-circuit indication;
- Periodic self-detection.


# DT Accessories DT-DBC4A1











## PARTS AND FUNCTIONS

**IN-USE:** Status indicator, it will light up when receives signal.

**POWER:** Working indicator, it will light up when plugs in power supply.

Impedance Switch: Video match switch, the last DBC4A1 at the end of the bus should set ON to match the video impedance, the power indicator will turn to orange after setting.

Bus: Input port, bus connection port.

**A,B,C,D:** Output port,connect to indoor monitors or door stations.

## **SPECIFICATION**

Power supply: DC20~30V

Temperature:  $-10^{\circ}\text{C} \sim +40^{\circ}\text{C}$ 

Wiring: 2 wires (non-polarity)

Dimension: 89\*70\*45mm